

**MODEL: R4KCB13 - SLIM CODE STATION**



R4KCB13

**FEATURES**

- Extra large back-lit button for easier activation
- Output for elapsed timer
- Call-Assurance/Monitor LED
- Cancel button
- Plug-in connectors for easy service
- Continuous supervision of station
- Optional antimicrobial Bio-seal to cover buttons and allow for easy disinfecting of station

**SPECIFICATIONS**

**Power Required:** 4mA @15VDC

**Power Required when used with SLIM Speaker Module:** 7mA @15VDC

**Weight:** 0.20 lbs. (0.09 kg)

**Size:** W: 3.2" (8.10 cm)

H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

**Housing and Finish:** High-impact molded Cycloy 2950 UL 94-5VB; light grey faceplate

**Controls/Indicators:** One (1) Push button for call actuation, One (1) Call-assurance/Monitor LED, and One (1) Cancel button

**Terminations:** Plug-on connectors

**Backbox Requirement:** 1-gang, (Non-gangable) W: 2.25" (5.7 cm) H: 4" (10.2 cm) D: 3.5" (8.9 cm)

**Backbox Requirement when used with SLIM Speaker Module:** 3-gang, Non-gangable W: 5.5" (14 cm) H: 3.75" (9.5 cm) D: 3.5" (8.9 cm)

**Certification:** Designed for compliance to UL/C-UL 1069, FCC Part 15 Class B, IEC60601-1 and IEC60601-1-2, CE Marking (MDD), FDA Registered, RoHS Compliant

**DESCRIPTION**

The Responder® 4000 SLIM Code Station is a call push-button station providing the ability to place a code call. Pressing the cancel button cancels the call. This station provides an output for an elapsed timer supporting a momentary or latched contact closure output. The Code Blue button is back-lit for easier location in a dark room. Using custom buttons, the stations can be customized for unique call-ins such as "Code Pink", and more.

The SLIM Code Station is connected to its associated corridor light and is continually supervised for station presence. Through programming, a "Trouble" message can annunciate at the associated console(s) when the

station is removed from the system. This station also offers enhanced supervision capabilities by notifying staff if the cancel button is depressed continuously (stuck) for long time. A "CB Fail" trouble message will annunciate at the associated console(s).

*Architect and Engineer (A&E) Specifications available online at: [customerconnection.rauland.com](http://customerconnection.rauland.com)  
Specifications subject to change without notice*

©Copyright 2009 Rauland-Borg Corporation Printed in USA Rev 03/2009