

MODEL: R5K DUAL 1/4" JACK STATION



R4K2JACK



FEATURES

- Two (2) inputs for dry contact auxiliary alarms with call-assurance LEDs and Monitor LED
- Compatible with various dry contact 1/4" jack-compatible medical instruments
- Cancel button
- Annunciate medical equipment alarms on pocket pagers, wireless phones, consoles, etc
- Each input can be configured as momentary or latched
- Continuous supervision of station
- Optional antimicrobial Bio-seal to cover cancel button and allow for easy disinfecting of the station
- Annunciates cord-out
- No dummy plug required
- With optional speaker module, can be used as dual bed station.

SPECIFICATIONS

Power Required: 22mA @15VDC

Power Required when used with Speaker Module:
 25mA @ 15VDC

Weight: 0.2 lbs. (0.09 kg)

Size: W: 3.2" (8.1 cm)

H: 4.25" (10.8 cm)

D: 0.6" (1.5 cm) in back box: 0.5" (1.3 cm) off-wall

Housing and Finish: High-impact molded Cycloy 2950 UL 94-5VB; light grey faceplate

Controls/Indicators: Two (2) 1/4" jacks, One (1)

Call-Assurance LED, and One (1) Call-Assurance/Monitor LED, and One (1) Cancel button

Terminations: Plug-on connector

Backbox Requirement: 1-gang, Non-gangable [W: 2.25" (5.7 cm) H: 4" (10.2 cm) D: 3.5" (8.9 cm)]

Backbox Requirement when used with Speaker

Module: 3-gang, Non-gangable [W: 5.5" (14 cm) H: 3.75" (9.5 cm) D: 3.5" (8.9 cm)]

Certification: Designed for compliance to ANSI/UL 1069, IEC 60950, CE, RoHS / WEEE Compliant. Assembled in a U.S. FDA Registered facility.

DESCRIPTION

The Responder® 5000 2 Jack Station provides the ability to place two unique call priorities from a single station. The station is typically installed in patient rooms and monitors medical equipment that is routinely used. The 2 Jack Station allows an alarm from patient monitoring equipment to light corridor lights, tone and display at a console, as well as directly alert caregivers carrying wireless devices. Each 1/4" jack is supervised, so if a piece of equipment is unplugged a call will be placed.

When used in conjunction with optional Responder® 5000 Speaker Module, the station can be used as dual bed

station with CC200 or equivalent 1/4" Call Cords to place call-ins. Cord Out signal is provided when a call cord is removed from its jack. The LED by the left jack turns green or yellow, providing monitor function, when the speaker is active.

The 2 Jack Station is connected to its associated corridor light and is continually supervised for station presence. Through programming, a "Trouble" message can annunciate at the associated console(s) when the station is removed from the system.