# Responder® Health Care Communications Systems

# MODEL: R4K21V — DUAL PATIENT STATION







R4K21V

#### **F**EATURES

- · Over four (4) call-in priorities available
- Two (2) DIN receptacles for patient nurse call & entertainment controls
- · Two (2) Call-Assurance LEDs with Cancel button
- · No dummy plugs required
- · Continuous supervision for station presence
- · Plug-in connectors for easy service
- Unique mounting plate design accommodates a variety of single and dual gang backboxes

# **SPECIFICATIONS**

Power Required: 15.5V DC @ 4mA

Weight: 0.20 lb. (0.09 kg)
Size: W: 4.21" (10.69 cm)
H: 5.46" (13.87 cm)
D: 1.17" (2.97 cm)

Housing & Finish: High-impact molded ABS94VO;

light gray faceplate

Controls: Two (2) DIN receptacles

One (1) Cancel button

One (1) Monitor LED indicator Two (2) Call-Assurance indicators Terminations: Plug-on connectors

Backbox Options: Raco 561, Steel City 58371 3/4R or any

other single gang backbox. Mounting plate allows for North American, South American, and European style single

and dual gang backboxes

Certification: UL/C-UL 1069; CE.

### **DESCRIPTION**

The R4K12V — Dual Patient Station is a dual bed station typically used in a visual system. The station allows both patients and staff to place different call-in priorities, depending on their requirements, to the assigned console(s). The bed stations can interface with call cords and entertainment speakers to initiate calls and provide entertainment control.

The bedside station is connected to its associated corridor light or domeless room controller and is continually supervised for station presence. Through programming, a "Sta-

tion Out" call can annunciate at the associated console(s) when the station is removed from the system.

## ASSOCIATED EQUIPMENT

CLV122 / CLV144 — Visual Corridor Lights

DCV100 / DCV116 — Visual Domeless Room Controllers

**Pillow Speakers** 

CCDIN — Call Cord

Architect and Engineer (A&E) Specifications available online at: customerconnection.rauland.com Specifications subject to change without notice

©Copyright 2014 Rauland-Borg Corporation Printed in USA Rev 04/2014



